AC214 Series



Low Frequency Accelerometer, Top Exit 2 Pin Connector, 1,000 mV/g, \pm 5%






Product Features


Designed for Low Speed Rotors, Wind Turbine Main Bearings, Gear Box Inputs, and May Also Be Used for High Frequency Detection.


May be used with any application that requires low and high frequency measurements.


- ▶ 1000 mV/g Sensitivity
- ▶ 0.1 Hz to 10 kHz Frequency Response (± 3dB)
- Standard 2 Pin MIL Connection or Integral Cable

Note: Integral Cable Options are only for Permanent Monitoring Applications









	Stockiio	Stock Froduct		Built 10 Order		
	Specifications	Standard		Metric		
ı	Part Number	AC214		M/ or M8/AC214		
	Sensitivity (±5%)		1000 mV/g			
	Frequency Response (±3dB)	6-600,000 CPM		0,1-10000 Hz		
	Frequency Response (±10%)	18-480,000 CPM		0,3-8000 Hz		
	Dynamic Range		± 7 g, peak *Vsource ≥ 22V, 12Vbias			
į	<u>Electrical</u>					
	Settling Time		< 2 seconds			
	Voltage Source (IEPE)		18-30 VDC			
	Constant Current Excitation		2-10 mA			
	Spectral Noise @ 10 Hz		1.3 μg/√Hz			
	Spectral Noise @ 100 Hz		0.2 μg/√Hz			
	Spectral Noise @ 1000 Hz		0.1 μg/√Hz			
	Output Impedance		< 100 ohm			
	Bias Output Voltage		10-14 VDC			
	Case Isolation		> 10 ⁸ ohm			

	Specifications	Standard		Metric
4	<u>Environmental</u>			
	Operating Temperature Range	-58 to 250 °F		-50 to 121 °C
	Maximum Shock Protection		5000 g, peak	
	Electromagnetic Sensitivity		CE	
	Sealing		Welded, Hermetic	
	Submersible Depth	200 ft.		60 m
	SIL Rating		SIL 2	
	<u>Physical</u>			
	Sensing Element		PZT Ceramic	
	Sensing Structure		Shear Mode	
	Weight	3.25 oz		92 g
	Case Material		316L Stainless	
			Steel	
	Mounting Thread		1/4-28 Blind	
	Modning Thread		Tapped Hole	
	Connector (Non-Integral)		2 Pin MIL-C-5015	
	Resonant Frequency	1,020,000 CPM		17000 Hz
	Mounting Torque	2 to 5 ft. lbs.		2.7 to 6.8 Nm
	Mounting Hardware Supplied	1/4-28 Stud		M6x1 or M8x1.25
	Mounting Haraware Supplied	1/4-20 Stud		Adapter Stud
	Calibration Certificate		CA10	

Typical Frequency Response

